#### LFT

# Linear Control Systems (036012) chapter 5

#### Leonid Mirkin

Faculty of Mechanical Engineering Technion—IIT



### Outline

System interconnections

Linear fractional transformations

### Control as interconnections

- control is about changing behavior of systems
- two options
  - 1. redesign
  - 2. interact

### Control as interconnections

- control is about changing behavior of systems
- two options
  - 1. redesign
  - 2. interact

# Basic interconnections



Main questions:

- how interactions change properties?
- when degrees are preserved?

Assume:

$$G_1(s) = \begin{bmatrix} A_1 & B_1 \\ \hline C_1 & D_1 \end{bmatrix} \text{ and } G_2(s) = \begin{bmatrix} A_2 & B_2 \\ \hline C_2 & D_2 \end{bmatrix}$$

are minimal realizations of order  $n_1$  and  $n_2$ , respectively.

### Parallel interconnections



Realization modes are the union of those of its components. Minimality?

Unobservable modes:

$$0 = \begin{bmatrix} A_1 - \lambda I & 0 \\ 0 & A_2 - \lambda I \\ C_1 & C_2 \end{bmatrix} \begin{bmatrix} \eta_1 \\ \eta_2 \end{bmatrix} = \begin{bmatrix} (A_1 - \lambda I)\eta_1 \\ (A_2 - \lambda I)\eta_2 \\ C_1\eta_1 + C_2\eta_2 \end{bmatrix}$$

- $\eta_1 \neq 0 \text{ and } \eta_2 \neq 0 \qquad \qquad \text{by observability of } (C_1, A_1) \text{ and } (C_2, A_2)$
- $\ \lambda \in \operatorname{spec}(A_1) \cap \operatorname{spec}(A_2)$
- $\quad C_1 \ker (\lambda I A_1) \cap C_2 \ker (\lambda I A_2) \neq \{0\}$

## Parallel interconnections (contd)

### Proposition

Suppose that both  $(A_1, B_1, C_1, D_1)$  and  $(A_2, B_2, C_2, D_2)$  are minimal. The realization of their parallel interconnection is controllable iff

$$\operatorname{pdir}_{i}(G_{1},\lambda) \cap \operatorname{pdir}_{i}(G_{2},\lambda) = \{0\}$$

and is observable iff

$$\mathsf{pdir}_o(G_1,\lambda) \cap \mathsf{pdir}_o(G_2,\lambda) = \{0\},\$$

both for all  $\lambda \in \operatorname{spec}(A_1) \cap \operatorname{spec}(A_2)$ .

### Cascade interconnections

$$y_{-} G_{2} - G_{1} - u = \begin{bmatrix} A_{1} & 0 & B_{1} \\ B_{2}C_{1} & A_{2} & B_{2}D_{1} \\ D_{2}C_{1} & C_{2} & D_{2}D_{1} \end{bmatrix}$$

Realization modes are the union of those of its components. Minimality? Unobservable modes:

$$0 = \begin{bmatrix} A_1 - \lambda I & 0 \\ B_2 C_1 & A_2 - \lambda I \\ D_2 C_1 & C_2 \end{bmatrix} \begin{bmatrix} \eta_1 \\ \eta_2 \end{bmatrix} = \begin{bmatrix} I & 0 & 0 \\ 0 & A_2 - \lambda I & B_2 \\ 0 & C_2 & D_2 \end{bmatrix} \begin{bmatrix} (A_1 - \lambda I)\eta_1 \\ \eta_2 \\ C_1\eta_1 \end{bmatrix}$$
  

$$- \eta_1 \neq 0 \qquad \qquad \text{by observability of } (C_2, A_2)$$
  

$$- \lambda \in \text{spec}(A_1)$$
  

$$- (A_1 - \lambda I)\eta_1 = 0 \text{ and } \begin{bmatrix} A_2 - \lambda I & B_2 \\ C_2 & D_2 \end{bmatrix} \begin{bmatrix} \eta_2 \\ C_1\eta_1 \end{bmatrix} = 0$$
  

$$- C_1 \ker(\lambda I - A_1) \cap \begin{bmatrix} 0 & I \end{bmatrix} \ker R_{G_2}(\lambda) \neq \{0\}$$

## Cascade interconnections (contd)

### Proposition

Suppose that both  $(A_1, B_1, C_1, D_1)$  and  $(A_2, B_2, C_2, D_2)$  are minimal. The realization of their cascade interconnection is controllable iff

$$\operatorname{pdir}_i(G_2,\lambda) \cap \operatorname{zdir}_o(G_1,\lambda) = \{0\}$$

for all  $\lambda \in \text{spec}(A_2)$  and is observable iff

$$\operatorname{zdir}_{i}(G_{2},\lambda) \cap \operatorname{pdir}_{o}(G_{1},\lambda) = \{0\},\$$

for all  $\lambda \in \operatorname{spec}(A_1)$ .

Benauto:  $zdir_{s}(G_{1}, k)$  and  $zdir_{s}(G_{2}, k)$  might be nontrivial even if k is not a zero of  $G_{1}$  and  $G_{2}$ , respectively. If mank( $R_{2}$ , (z))  $\approx m + p_{1}$ , but the cause  $m_{1} \ll p_{2}$  or because of its normal rank densions,  $zdir_{s}(G_{1}, z)$  is nontrivial for all z. Likewise, if mank( $R_{2}$ , (z))  $\approx m + m_{2}$  for whatever massing  $zdir_{s}(G_{2}, z)$  is nontrivial for all z. Likewise, if month( $R_{2}$ , (z))  $\approx m + m_{2}$  for whatever massing  $zdir_{s}(G_{2}, z)$  is nontrivial for all z taken to be a second to be

## Cascade interconnections (contd)

### Proposition

Suppose that both  $(A_1, B_1, C_1, D_1)$  and  $(A_2, B_2, C_2, D_2)$  are minimal. The realization of their cascade interconnection is controllable iff

$$\operatorname{pdir}_i(G_2,\lambda) \cap \operatorname{zdir}_o(G_1,\lambda) = \{0\}$$

for all  $\lambda \in \text{spec}(A_2)$  and is observable iff

$$\operatorname{zdir}_{i}(G_{2},\lambda) \cap \operatorname{pdir}_{o}(G_{1},\lambda) = \{0\},\$$

for all  $\lambda \in \operatorname{spec}(A_1)$ .

Remark:  $zdir_o(G_1, \lambda)$  and  $zdir_i(G_2, \lambda)$  might be nontrivial even if  $\lambda$  is not a zero of  $G_1$  and  $G_2$ , respectively. If nrank $(R_{G_1}(s)) < n_1 + p_1$ , be it because  $m_1 < p_1$  or because of its normal rank deficiency,  $zdir_o(G_1, s)$  is nontrivial for all s. Likewise, if nrank $(R_{G_2}(s)) < n_2 + m_2$  for whatever reason,  $zdir_i(G_2, s)$  is nontrivial for all s too. Hence, if G(s) has its McMillan degree below  $n_1 + n_2$ , we call it just "cancellation," rather than "pole-zero cancellation."

### Feedback interconnections

If  $D_2 = 0$  (simplicity), then



Realization modes are unrelated to those of its components. Minimality?

Observability PBH:

$$\begin{bmatrix} A_1 - \lambda I & B_1 C_2 \\ B_2 C_1 & A_2 + B_2 D_1 C_2 - \lambda I \\ C_1 & D_1 C_2 \end{bmatrix} = \begin{bmatrix} I & 0 & 0 \\ 0 & I & B_2 \\ 0 & 0 & I \end{bmatrix} \begin{bmatrix} A_1 - \lambda I & B_1 C_2 \\ 0 & A_2 - \lambda I \\ C_1 & D_1 C_2 \end{bmatrix}$$

Hence

- observability here is lost iff it's lost in  $G_1G_2$ 

## Feedback interconnections (contd)

### Proposition

Suppose that both  $(A_1, B_1, C_1, D_1)$  and  $(A_2, B_2, C_2, D_2)$  are minimal and that det $(I - D_1D_2) \neq 0$ . The realization of their feedback interconnection is controllable iff

$$\operatorname{pdir}_i(G_2,\lambda) \cap \operatorname{zdir}_o(G_1,\lambda) = \{0\}$$

and is observable iff

$$\operatorname{zdir}_{i}(G_{1},\lambda) \cap \operatorname{pdir}_{o}(G_{2},\lambda) = \{0\},\$$

both for all  $\lambda \in \operatorname{spec}(A_2)$ .

System interconnections

LFT

### Outline

System interconnections

Linear fractional transformations

U1

 $\overline{u}_2$ 

### LFT



The lower LFT  $\mathcal{F}_{\mathsf{I}}(H, G) : u_1 \mapsto y_1$  reads

 $\mathcal{F}_{\mathsf{I}}(H,G) = G_{11} + G_{12}H(I - G_{22}H)^{-1}G_{21} = G_{11} + G_{12}(I - HG_{22})^{-1}HG_{21}$ 

The upper LFT  $\mathcal{F}_u(H, G) : u_2 \mapsto y_2$  reads

 $\mathcal{F}_{u}(G,H) = G_{22} + G_{21}(I - HG_{11})^{-1}HG_{12} = G_{22} + G_{21}H(I - G_{11}H)^{-1}G_{12}$ 

Moreover,

$$\mathcal{F}_{\mathsf{u}}(G,H) = \mathcal{F}_{\mathsf{I}}\left(\left[\begin{smallmatrix}0 & I\\ I & 0\end{smallmatrix}\right]G\left[\begin{smallmatrix}0 & I\\ I & 0\end{smallmatrix}\right],H\right)$$

#### Parallel:

 $G_1 + G_2 = \mathcal{F}_{\mathsf{I}} \left( \begin{bmatrix} G_1 & I \\ I & 0 \end{bmatrix}, G_2 \right)$ 

Series:

Feedback:

 $\mathbf{G}_{1}(\mathbf{I} - \mathbf{G}_{2}\mathbf{G}_{1})^{-1} = \mathcal{F}_{1}\left( \left[ egin{array}{cc} \mathbf{G}_{1} & \mathbf{G}_{1} \\ \mathbf{G}_{1} & \mathbf{G}_{1} \end{array} 
ight], \mathbf{G}_{2} 
ight)$ 

GoF (positive feedback):

 $\begin{bmatrix} T_{c} & T_{i} \\ S_{o} & T_{d} \end{bmatrix} := \begin{bmatrix} R \\ I \end{bmatrix} (I - PR)^{-1} \begin{bmatrix} I & P \end{bmatrix} = \mathcal{F}_{1} \begin{pmatrix} \begin{bmatrix} 0 & 0 & i & I \\ I & P & P \\ I & P & P \end{bmatrix}, R$ tate-space realization:

 $\begin{bmatrix} A & B \\ \hline C & D \end{bmatrix} = \mathcal{F}_0 \left( \begin{bmatrix} A & B \\ C & D \end{bmatrix}, \frac{1}{s}^l \right)$ 

Parallel:

 $G_1 + G_2 = \mathcal{F}_I \left( \left[ \begin{array}{cc} G_1 & I \\ I & 0 \end{array} \right], G_2 \right)$ 

Series:

$$G_2G_1 = \mathcal{F}_{\mathsf{I}}\left(\left[\begin{array}{cc} 0 & I\\ G_1 & 0\end{array}\right], G_2\right)$$

Feedback:

 $G_1(I - G_2 G_1)^{-1} = \mathcal{F}_1 \left( \begin{bmatrix} G_1 & G_1 \\ G_1 & G_1 \end{bmatrix}, G_2 \right)$ 

GoF (positive feedback):

 $\begin{bmatrix} T_{c} & T_{i} \\ S_{o} & T_{d} \end{bmatrix} \coloneqq \begin{bmatrix} R \\ I \end{bmatrix} (I - PR)^{-1} \begin{bmatrix} I & P \end{bmatrix} = \mathcal{F}_{i} \begin{pmatrix} 0 & 0 & i & I \\ I & P & P \\ \hline I & P & P \end{bmatrix}, R$ tate-space realization:

 $\begin{bmatrix} A & B \\ \hline C & D \end{bmatrix} = \mathcal{F}_{u} \left( \begin{bmatrix} A & B \\ C & D \end{bmatrix}, \frac{1}{s}' \right)$ 

Parallel:

$$G_1 + G_2 = \mathcal{F}_{\mathsf{I}}\left(\left[\begin{array}{cc}G_1 & I\\ I & 0\end{array}\right], G_2\right)$$

Series:

$$G_2 G_1 = \mathcal{F}_{\mathsf{I}} \left( \left[ \begin{array}{cc} 0 & I \\ G_1 & 0 \end{array} \right], G_2 \right)$$

Feedback:

$$G_1(I - G_2G_1)^{-1} = \mathcal{F}_I\left(\left[egin{array}{cc} G_1 & G_1 \ G_1 & G_1 \end{array}
ight], G_2
ight)$$

GoF (positive feedback):

 $\begin{bmatrix} T_{c} & T_{i} \\ S_{o} & T_{d} \end{bmatrix} := \begin{bmatrix} R \\ I \end{bmatrix} (I - PR)^{-1} \begin{bmatrix} I & P \end{bmatrix} = \mathcal{F}_{i} \left( \begin{bmatrix} 0 & 0 & I \\ I & P & P \\ I & P & P \end{bmatrix}, R \right)$ State-space realization:

$$\begin{bmatrix} A & B \\ \hline C & D \end{bmatrix} = \mathcal{F}_{0} \left( \begin{bmatrix} A & B \\ C & D \end{bmatrix}, \frac{1}{s}' \right)$$

Parallel:

$$G_1 + G_2 = \mathcal{F}_{\mathsf{I}}\left(\left[\begin{array}{cc}G_1 & I\\ I & 0\end{array}
ight], G_2
ight)$$

Series:

$$G_2 G_1 = \mathcal{F}_{\mathsf{I}} \left( \left[ \begin{array}{cc} 0 & I \\ G_1 & 0 \end{array} \right], G_2 \right)$$

Feedback:

$$G_1(I - G_2 G_1)^{-1} = \mathcal{F}_I \left( \left[ egin{array}{cc} G_1 & G_1 \ G_1 & G_1 \end{array} 
ight], G_2 
ight)$$

GoF (positive feedback):

$$\begin{bmatrix} T_{c} & T_{i} \\ S_{o} & T_{d} \end{bmatrix} := \begin{bmatrix} R \\ I \end{bmatrix} (I - PR)^{-1} \begin{bmatrix} I & P \end{bmatrix} = \mathcal{F}_{I} \left( \begin{bmatrix} 0 & 0 & I \\ I & P & P \\ I & P & P \end{bmatrix}, R \right)$$

 $\begin{bmatrix} A & B \\ \hline C & D \end{bmatrix} = \mathcal{F}_{\mathfrak{p}} \left( \begin{bmatrix} A & B \\ C & D \end{bmatrix}, \frac{1}{s} l \right)$ 

Parallel:

$$G_1 + G_2 = \mathcal{F}_{\mathsf{I}}\left(\left[\begin{array}{cc}G_1 & I\\ I & 0\end{array}\right], G_2\right)$$

Series:

$$G_2 G_1 = \mathcal{F}_{\mathsf{I}} \left( \left[ \begin{array}{cc} 0 & I \\ G_1 & 0 \end{array} \right], G_2 \right)$$

Feedback:

$$G_1(I - G_2G_1)^{-1} = \mathcal{F}_I\left(\left[egin{array}{cc} G_1 & G_1 \ G_1 & G_1 \end{array}
ight], G_2
ight)$$

GoF (positive feedback):

$$\begin{bmatrix} T_{c} & T_{i} \\ S_{o} & T_{d} \end{bmatrix} := \begin{bmatrix} R \\ I \end{bmatrix} (I - PR)^{-1} \begin{bmatrix} I & P \end{bmatrix} = \mathcal{F}_{I} \left( \begin{bmatrix} 0 & 0 & I \\ I & P & P \\ I & P & P \end{bmatrix}, R \right)$$

State-space realization:

$$\left[\frac{A \mid B}{C \mid D}\right] = \mathcal{F}_{\mathsf{u}}\left(\left[\begin{array}{cc}A & B\\C & D\end{array}\right], \frac{1}{s}I\right)$$

# Well posedness

#### Clearly,

$$I - G_{22}H$$
 is invertible  $\implies \mathcal{F}_{I}(G, H)$  is well defined

### Example

The LFT

$$\mathcal{F}_{\mathsf{I}}\left(\left[\begin{array}{rrr}1:0&1\\1:\alpha&0\\0:0&0\end{array}\right],I\right)=1,\quad\forall\alpha$$

although

$$I - G_{22}H = \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} - \begin{bmatrix} \alpha & 0 \\ 0 & 0 \end{bmatrix} = \begin{bmatrix} 1 - \alpha & 0 \\ 0 & 1 \end{bmatrix}$$

is singular for  $\alpha = 1$ .

$$\left[egin{array}{cc} 1-lpha & 0 \ 0 & 1 \end{array}
ight] u_2 = \left[egin{array}{cc} 1 \ 0 \end{array}
ight] u_1,$$

is not well defined under lpha=1.

### Well posedness

#### Clearly,

$$I - G_{22}H$$
 is invertible  $\implies \mathcal{F}_{I}(G, H)$  is well defined

### Example

The LFT

$$\mathcal{F}_{\mathsf{I}}\left( \left[ egin{array}{ccc} 1 & 0 & 1 \ 1 & lpha & 0 \ 0 & 0 & 0 \end{array} 
ight], I 
ight) = 1, \quad orall lpha$$

although

$$I - G_{22}H = \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix} - \begin{bmatrix} \alpha & 0 \\ 0 & 0 \end{bmatrix} = \begin{bmatrix} 1 - \alpha & 0 \\ 0 & 1 \end{bmatrix}$$

is singular for  $\alpha = 1$ . But (internal signal)  $u_2$ , satisfyng

$$\left[\begin{array}{cc} 1-\alpha & 0\\ 0 & 1 \end{array}\right] u_2 = \left[\begin{array}{c} 1\\ 0 \end{array}\right] u_1,$$

is not well defined under  $\alpha = 1$ .

System interconnections

### Well posedness (contd)



LFT is well posed if all mappings  $v_i \mapsto e_j$  are well defined.



LFT

## Well posedness (contd)



LFT is well posed if all mappings  $v_i \mapsto e_j$  are well defined.

$$\begin{bmatrix} I & 0 & -G_{12} \\ 0 & I & -G_{22} \\ 0 & -H & I \end{bmatrix} \begin{bmatrix} e_1 \\ e_2 \\ e_3 \end{bmatrix} = \begin{bmatrix} G_{11} & 0 & 0 \\ G_{21} & I & 0 \\ 0 & 0 & I \end{bmatrix} \begin{bmatrix} v_1 \\ v_2 \\ v_3 \end{bmatrix}$$

$$\downarrow$$

$$\begin{bmatrix} I & -G_{22} \\ -H & I \end{bmatrix} \text{ is invertible}$$

$$\downarrow$$

$$I - G_{22}H \text{ is invertible} \iff I - HG_{22} \text{ is invertible}$$

# I/O inversion

Proposition

If  $\mathcal{F}_{I}\!\left(G,H\right)$  is square and  $G_{11}$  is nonsingular, then

$$[\mathcal{F}_{l}(G,H)]^{-1} = \mathcal{F}_{l}\left(\begin{bmatrix} G_{11}^{-1} & -G_{11}^{-1}G_{12} \\ G_{21}G_{11}^{-1} & G_{22} - G_{21}G_{11}^{-1}G_{12} \end{bmatrix}, H\right).$$

If  $\mathcal{F}_u(G, H)$  is square and  $G_{22}$  is nonsingular, then

$$[\mathcal{F}_u(G,H)]^{-1} = \mathcal{F}_u\left( \begin{bmatrix} G_{11} - G_{12}G_{22}^{-1}G_{21} & G_{12}G_{22}^{-1} \\ -G_{22}^{-1}G_{21} & G_{22}^{-1} \end{bmatrix}, H \right).$$

Proof (outline): The lower LFT relation follows by

$$\begin{bmatrix} y_1 \\ y_2 \end{bmatrix} = \begin{bmatrix} G_{11} & G_{12} \\ G_{21} & G_{22} \end{bmatrix} \begin{bmatrix} u_1 \\ u_2 \end{bmatrix} \iff \begin{bmatrix} u_1 \\ y_2 \end{bmatrix} = \begin{bmatrix} G_{11}^{-1} & -G_{11}^{-1}G_{12} \\ G_{21}G_{11}^{-1} & G_{22} - G_{21}G_{11}^{-1}G_{12} \end{bmatrix} \begin{bmatrix} y_1 \\ u_2 \end{bmatrix}$$
  
The upper LFT relation swaps  $y_2$  and  $u_2$ .

### T-H inversion

### Proposition

If G is invertible, with square and invertible  $G_{12}$  and  $G_{21}$ , then

$$T = \mathcal{F}_{l}(G, H) \iff H = \mathcal{F}_{u}(G^{-1}, T) = \mathcal{F}_{l}(\begin{bmatrix} 0 & l \\ l & 0 \end{bmatrix} G^{-1} \begin{bmatrix} 0 & l \\ l & 0 \end{bmatrix}, T).$$

Proof (outline): Relation follows by

$$T: u_1 \mapsto y_1$$
 in  $\begin{bmatrix} y_1 \\ y_2 \end{bmatrix} = G \begin{bmatrix} u_1 \\ u_2 \end{bmatrix}$  and  $u_2 = Hy_2$ ,

so

$$H: y_2 \mapsto u_2$$
 in  $\begin{bmatrix} u_1 \\ u_2 \end{bmatrix} = G^{-1} \begin{bmatrix} y_1 \\ y_2 \end{bmatrix}$  and  $y_1 = T u_1$ .

The invertibility of  $G_{12}$  and  $G_{21}$  is required to show the equivalence of the well-posedness properties of  $\mathcal{F}_{l}(G, H)$  and  $\mathcal{F}_{u}(G^{-1}, T)$ .

### Redheffer star product



 $\mathcal{F}_{\mathsf{I}}(G, \mathcal{F}_{\mathsf{I}}(\tilde{G}, H)) = \mathcal{F}_{\mathsf{I}}(G \star \tilde{G}, H).$ 

### Redheffer star product



SO

 $\mathcal{F}_{\mathsf{I}}\big(G,\mathcal{F}_{\mathsf{I}}\big(\tilde{G},H\big)\big)=\mathcal{F}_{\mathsf{I}}\big(G\star\tilde{G},H\big).$